

AUKEY

Basix Pro 10000mAh
Wireless Charging Power Bank
取扱説明書

AUKEY製品をお買い上げいただき、誠にありがとうございます。ご使用前にこの取扱説明書をよくお読みの上、正しくお使いください。また、お読みになった後は大切に保管してください。

パッケージ内容

本体
USB-C to Aケーブル
取扱説明書

製品図

- 01 -

ワイヤレス充電をご使用になる際は、モバイルバッテリー本体の中央にスマートフォンまたはタブレットを置いてください。

- 02 -

**ワイヤレス充電
LEDステータスインジケータ**

- 04 -

仕様

型番	PB-WL02
技術	Qi, Power Delivery 3.0, Quick Charge™ 3.0
容量	10000mAh / 37Wh
電池のタイプ	リチウムポリマー
USB-C 入力	(Power Delivery 3.0) DC 5V 3A / 9V 2A
USB-C 出力	(Power Delivery 3.0) DC 5V 3A / 9V 2A / 12V 1.5A
USB-A 出力	(Quick Charge™ 3.0) DC 5V 2.4A / 9V 2A / 12V 1.5A
ワイヤレス充電出力	5W, 7.5W, 10W
最大出力	18W
寸法	155 x 75 x 16mm
重量	242g

- 05 -

USBパワーデリバリー(PD)とは？

USB PDは、USB Type-C接続を介して自動的に電力出力をネゴシエートし、タブレットやノートパソコン、スマートフォンなどの互換性のある幅広い機器に対して、安全かつ効率的に充電を行うことのできる、マルチ電圧対応のUSB充電規格です。

USB PDで急速充電を利用する際は、以下の3点をご留意ください。

- USB PD対応の機器 (スマートフォン、タブレット、ノートパソコン)
- USB PD規格のUSB-C充電器
- USB-C to CケーブルまたはUSB-C to Lightningケーブル

Quick Charge™ 3.0とは？

Qualcomm® Quick Charge™ 3.0テクノロジーは、従来のUSB充電の最大4倍の速度でデバイスを充電するように設計されています。これは、Quick Charge™ 1.0の2倍の速さで、Quick Charge™ 2.0より38%高効率です。

- 06 -

ワイヤレス充電

モバイルバッテリー本体の中央にスマートフォンまたはタブレットを置いてください。

ご注意

- ワイヤレス充電モードをオンにするとき、USB-AおよびUSB-Cポートが未接続状態の場合は、5Wから開始された出力が、約15秒後に自動的に高速ワイヤレス充電モード(7.5W または10W出力)へ移行します。
- USB-AまたはUSB-Cポートに機器を接続して高速充電しているときに電源スイッチを押してワイヤレス充電を開始すると、そのポートは5Vに制限されます。Qi対応機器が検出されない場合、モバイルバッテリーは15秒後に自動的にワイヤレス充電モードを終了し、USB-AまたはUSB-Cポートの高速充電を再開します。

- 07 -

有線での充電

- 付属のUSB-C to Aケーブルをスマートフォンやタブレットなどの対応機器の充電ポートに接続してください。
- もう一方の端をモバイルバッテリー本体のUSB-Aポートに接続してください。
- 機器が完全に充電されたら、ケーブルを取り外してください。
※別売のUSB-C to Cケーブルを使用することも可能です。

ご注意

- 2つのポート(ワイヤレス充電を含む)が同時に出力されると、出力は自動的に高速充電モード(9V / 12V)をオフに、5Vで出力 (ワイヤレス充電は自動切換えで5W) になります。
- 本製品は、2つ以上の機器への同時充電をサポートします。(注：全出力電力が18Wを超える場合、放電をオフにする過電流保護を行います。これは通常の仕様です。)

- 08 -

- 本製品は、充電 (モバイルバッテリー本体の充電) と放電 (機器への出力) を同時にサポートすることができます。(注：充電および放電同時機能は5Vのみであり、高速充電出力には対応していません。)
- ※充電と放電を同時にサポートする機能は、アダプターがまず機器側を優先し、モバイルバッテリーには小電流でゆっくりと充電されます。アダプターの出力電力が出力装置に対応していなければ、充電されない場合があります。

- 09 -

製品のお手入れと使用上の注意

- 湿度が高い場所、極端に高温や低温の場所に長時間放置しないでください。
- 長期間使用しない場合でも、少なくとも3ヶ月に1度本体を充電してください。
- 強い衝撃を与えないでください。
- 加熱しないでください。
- 車の中に長時間放置しないでください。
- 分解・改造をしないでください。
- 以下の場合は直ちに使用を中止し、サポートセンターにご連絡ください。
 - 一層が出ている
 - 変な匂いが出る
 - 変形している
- 本製品を廃棄する時は、各自治体の指示に従った方法で、正しく廃棄してください。

- 10 -

Model: PB-WL02

jp.aukey.com

AUKEYからののお知らせ、最新情報をお届けします。

@AUKEY_jp @Aukey.jp @AUKEY JAPAN

AUKEY Technology Co., Ltd.
jp.aukey.com | japansupport@aukey.com
Room 102, Building P09, South China City
Electronics Trading Center, Longgang District,
Shenzhen, Guangdong, 518111, China

CE FC RoHS Made in China

株式会社 美資本

PBWL02200221A1000SE-M1

AUKEY

Basix Pro 10000mAh
Wireless Charging Power Bank
User Manual

Thank you for purchasing AUKEY products. Please read this user manual carefully and keep it for future reference.

Package Contents

Basix Pro Wireless Charging Power Bank
USB-C to A Cable
User Manual
Warranty Card

Getting Started

- 01 -

Place your phone or tablet on the center of your Basix Pro Wireless Charging Power Bank

- 02 -

Wireless Charging LED status indicator

- 04 -

Specifications

Model	PB-WL02
Technology	Qi, Power Delivery 3.0, Quick Charge 3.0
Capacity	10000mAh / 37Wh
Battery Type	Lithium polymer
USB-C Input	(Power Delivery 3.0) DC 5V 3A / 9V 2A
USB-C Output	(Power Delivery 3.0) DC 5V 3A / 9V 2A / 12V 1.5A
USB-A Output	(Quick Charge 3.0) DC 5V 2.4A / 9V 2A / 12V 1.5A
Wireless Charging Output	5W, 7.5W, 10W
Max Power Output	18W
Dimensions	155 x 75 x 16mm 6.10" x 2.95" x 0.61"
Weight	242g / 8.54oz

- 05 -

What is USB Power Delivery (PD)?

USB Power Delivery is a universal multi-voltage charging standard that dynamically negotiates power output over a USB Type-C connection to safely and efficiently recharge a wide range of compatible devices.

To get USB PD, the following are required

- Device (phone, tablet, laptop) that supports USB PD
- USB-C charger with USB PD
- USB-C to C cable or Apple USB-C to Lightning Cable

What is Quick Charge 3.0?

Charge compatible devices up to four times faster than conventional charging. Quick Charge 3.0 is engineered to refuel devices twice as fast as Quick Charge 1.0 and is up to 38% more efficient than Quick Charge 2.0. Backward-compatible with

- 06 -

Quick Charge 2.0/1.0 devices.

Wireless Charging

Place your phone or tablet on the center of your Basix Pro Wireless Charging Power Bank

Notes

- When the wireless charging mode is turned on, wireless charging will begin at 5W. If no devices are connected to the USB-A or USB-C port, output will automatically increase to 7.5W or 10W for compatible wireless fast charging devices after 15 seconds.
- If you press the power button to enter wireless charging mode while the USB-A or USB-C port is fast-charging your device, the output on that port will be limited to 5W. The power bank automatically exits wireless charging mode after 15 seconds if no Qi device is detected, and the USB-A or USB-C port will resume fast charging.

- 07 -

Wired Charging

- Connect the included USB-C to A cable to your device charging port.
- Connect the other end to the USB-C or USB-A output port on the PB-WL02.
- Unplug your device when fully charged.

Notes

- When any two ports (including wireless charging) are output at the same time, the output will automatically turn off the fast charging mode (9V / 12V). Enter 5V output power mode (wireless automatic switching 5W)
- The product supports simultaneous output of more than two devices. (Note: If the total output power exceeds 18W, the product will activate over-current protection to turn off discharging of any output, it is normal situation)

- 08 -

Product Care & Use

- Keep away from liquids and extreme heat.
- Recharge the PB-WL02 at least once every 3 months.
- Dispose of battery according to local environmental law.

- 09 -

Model: PB-WL02

jp.aukey.com

AUKEYからののお知らせ、最新情報をお届けします。

@AUKEY_jp @Aukey.jp @AUKEY JAPAN

AUKEY Technology Co., Ltd.
jp.aukey.com | japansupport@aukey.com
Room 102, Building P09, South China City
Electronics Trading Center, Longgang District,
Shenzhen, Guangdong, 518111, China

CE FC RoHS Made in China

株式会社 美資本